

Cable KVM Switch

LS Series

Introduction:

- *Operate two USB computers with one keyboard, mouse and monitor.
- *Simply plug the attached cables-nothing else required.
- *Full keyboard and mouse emulation for error-free booting.
- *Hot key commands and LED indicators for computer selection.
- *No software and power required.
- *Support video resolution up to 2048*1536.
- *Compatible with all operating systems.



Specification:

Type		LS-21JS	LS-21JA	LS-21CS	LS-21CA
Computer Connections		2	2	2	2
Port Selection		Hot-key (CTRL Twice)			
Console Ports	Keyboard, Mouse	2 x USB-A		1*6pin mini-DIN Female (PS/2)	
	Audio	/	1 x 3.5mm audio jack	/	1 x 3.5mm audio jack
	Video	1 x VGA 15HDS input		1 x VGA 15HDS input	
KVM Ports	Keyboard, Mouse	2 x USB-A		2*6pin mini-DIN Female (PS/2)	
	Audio	/	2 x 3.5mm audio jack	/	2 x 3.5mm audio jack
	Video	2 x VGA 15HDF output		2 x VGA 15HDF output	
LED' s	Selected	2 (Green)		2 (Green)	
Cable Length	Computers	2 x 1.2m		2 x 1.2m	
Video Resolution		2048*1536 (max); DDC2B		2048*1536 (max); DDC2B	
Switch Mode		Front Panel, Hot Key, Auto-Scan(3seconds)		Front Panel, Hot Key, Auto-Scan(3seconds)	
Operating Temperature		-10~50℃		-10~50℃	
Storing Temperature		-20~60℃		-20~60℃	
Housing		Plastic(Mini KVM)		Plastic(Mini KVM)	
Weight		360g(2ports)			
Dimension(L x W x H)		88*75*26mm			